

MAPSSIC, a CMOS Intra-Cerebral Probe for Brain Imaging in Awake and Freely Moving Rat

Luis Ammour, J. Heymes, M. Bautista, S. Fieux, M. Kachel, F. Gensolen,
A. Dubois F. Lefebvre, F. Pain, P. Pangaud, L. Pinot, J. Baudot, P.
Gisquet-Verrier, P. Laniece, C. Morel, L. Zimmer, M.-A. Verdier

*Fifth French-Ukrainian workshop on the instrumentation developments
for HEP*


*LAL, Orsay, France
November 6 – 8, 2017*




How anesthesia affects neuroimaging?

How to study molecular processes and behavior simultaneously?

RatCAP




Motion tracking



Spangler-Bickell *et al.*, *Phys. Med. Biol.*, 2016.


Schulz *et al.*, *Nature Methods*, 2011.

Beta Microprobe




Pain *et al.*, *PNAS*, 2002.

To develop a pixelated β^+ sensitive imaging device



To limit sensitivity to annihilation γ rays and visible light


To study fully freely-moving rodents



- ✓ good sensitivity to β^+
- ✓ Pixelated structure (10 pixels)
- ✓ Wireless communication




Fully freely moving animal with PIXSIC





A: Pixelated probe ; B : Readout electronic ; C : Battery and communication system

Several experiments validated PIXSIC biological and pharmacological suitability.



Evaluation of the tracer spatial distribution validated !


Several experiments validated PIXSIC biological and pharmacological suitability.



[18F]-MPPF 2 mCi injection - Hippocampus and cerebellum implantations.

Uptake measurement validated !

Several experiments validated PIXSIC biological and pharmacological suitability.



[^{11}C]-raclopride 2 mCi injection - Striatum and cerebellum implantations.

PIXSIC shows anesthesia bias on neuroimaging results !

PIXSIC: It works!


- First autonomous β^+ probe
- Validated in pharmacological studies
- Biocompatibility validated

... but it shows major limits :

- Mechanical robustness.
- Electronic noise.
- γ rays sensitivity.

CMOS MAPS technology

- Highly pixelated sensors
- Direct amplification on the pixel
- Data processing on the sensor
- Low thickness of the sensitive volume



Charged particles detection in MAPS

MAPSSIC project aims to:

- Develop a CMOS MAPS sensor
- Develop front-end electronics
- Create an autonomous system on the animal head and back
- Validate the biological compatibility (temperature, size ...)
- Ensure mechanical and electrical robustness


First prototype

- 18 μm sensitive layer
- digital sensor
- 1 bit memory per pixel per frame
- Low power consumption (160 μW)

Monte Carlo simulations





Experimental measurements



MAPSSIC sensor photography


Monte-Carlo simulations

Geometry of the simulation



Radioactive sources



- Homogeneous sources: ^{18}F , ^{11}C and ^{15}O
- Water cylinder : $H=30\text{ mm}$, $R=23\text{ mm}$
- Ability to modify *a posteriori* the activity distribution



Direct β^+ detection efficiency (left) and indirect detection efficiency (right) (^{18}F in water)

Results


- Low indirect detection efficiency, decreasing with distance to the sensor
- Volume $> 1\%$ efficiency is comparable to cerebral structures of interest




Sensitivity as a function of source radius and pixels sensitivity map

Results

- Sensitivity to β^+ ((events/s)/(Bq/mL)) | 18F | 11C | 15O
0.88 | 1.79 | 4.34
- Over the same sensor height, MAPSSIC sensor is 21% more sensitive than PIXSIC
- Integral non-uniformity: 7.53%





Structure name	Direct sens. ((evts/s)/(Bq/mm3)) contribution to the total	Indirect sens. ((evts/s)/(Bq/mm3)) contribution to the total
R.O.B.	$7.19 \times 10^{-2} \pm 0.21 \times 10^{-2}$ 7.67%	$1.42 \times 10^{-2} \pm 0.01 \times 10^{-2}$ 25.8%
Cereb.	$< 1 \times 10^{-5}$	$3.60 \times 10^{-4} \pm 0.15 \times 10^{-4}$ 0.65%
L. CPU.	$8.66 \times 10^{-1} \pm 0.01 \times 10^{-1}$ 92.3 %	$2.98 \times 10^{-2} \pm 0.01 \times 10^{-2}$ 54.1%
R. CPU.	$< 1 \times 10^{-5}$	$2.38 \times 10^{-3} \pm 0.14 \times 10^{-3}$ 4.32%
L. HG.	$< 1 \times 10^{-5}$	$3.03 \times 10^{-3} \pm 0.04 \times 10^{-3}$ 5.51%
R. HG.	$< 1 \times 10^{-5}$	$5.27 \times 10^{-3} \pm 0.06 \times 10^{-3}$ 9.57%



Deposited energy in pixels (^{18}F in water)

Results

- Peak $\approx 7 \text{ keV} \rightarrow$ energy threshold will be critical
- 24.3% of the γ spectrum is under 4 keV, 7.15% for the β^+ spectrum




Sensor sensitivity as a function of sensitive thickness


Results

- 18 μm is the best thickness for direct β^+ detection over indirect detection (1.58 times better than 190 μm)
- But sensitivity is reduced by a factor 2.34

The ratio between direct β^+ detection and indirect detection is not always maximum at lowest thickness values



Optimal thickness for a given energy threshold




Sensitivity as a function of pixels dimensions and energy threshold

Results

- Without energy threshold, pixels dimensions doesn't affect sensitivity
- With threshold, variations still limited. (10 keV threshold → 17% increase of sensitivity with a $\times 128$ pixel surface increase)

Experimental testings on first prototype


Experimental testing setup



→ Mean clusters size
(¹⁸F): 3.57 pixels
→ Most clusters (38%)
are 1 pixel large



Left: ⁵⁵Fe X-ray source image
Right: ¹⁸F beta⁺ source image

- 18F liquid sources (FDG or AV-1451) into an ABS container
- First MAPSSIC sensor prototype
- XBee microcontroller with Zigbee communication capability (450 ms duration frames)





Left: scattered clusters example.
Right: Piled-up clusters example.
Dots are local maxima found by our image processing algorithm

- Removal of noisy pixels based on their relative activation frequency
- Filtering with a 3×3 gaussian kernel ($\sigma = 1$)
- Searching for local maxima within 3×3 kernels




Results

- Events pile-up at high count rates (over 40 events/frame)
- Accordance with MC simulation in the linear region (2% difference)



Results

- Attenuation in polystyrene follows an exponential decay law with a linear coefficient $\mu_{exp} = 2.82 \pm 0.18 \text{ mm}^{-1}$
- Good agreement with empirical formulas ($\mu_{th} = 2.84 \text{ mm}^{-1}$)





Results

- The mean value on the edge is 2.92 times higher than the central region
- In the central region, the mean value of the two central columns is 19.5 % higher than the mean value of the other ones

- Merging sensors back to back to increase the implant sensitivity and efficiency
- Parylene cover to protect the sensor from moisture
- Head PCB for connecting the sensors
- Autonomous module and wireless communication
- New optimized sensor design based on the first experimental feedbacks
- More realistic Monte Carlo simulations
- Experimental measurements into water phantom then into brain tissues

- We successfully built a CMOS sensor β^+ for intracerebral β^+ microprobes
- Monte Carlo simulation demonstrated its suitability for in-vivo measurements
- Experimental testings confirmed its ability to measure β^+ emissions



Thank you for your attention

IMNC, Orsay

L. Ammour,
F. Lefebvre,
F. Pain,
L. Pinot,
P. Laniece,
M.-A. Verdier

*IPHC,
Strasbourg*

J. Heymes,
M. Kachel,
J. Baudot

*CPPM,
Marseille*

M. Bautista,
F. Gensolen,
P. Pangaud,
C. Morel

CRNL, Lyon

S. Fieux,
L. Zimmer

*NeuroPSI,
Orsay*

P. Gisquet-Verrier



PARIS
SUD
DIDEROT



Mission interdisciplinarité
Centre national de la recherche scientifique

Institut national de physique nucléaire et de physique des particules
Centre national de la recherche scientifique